



# vLoc3-MLA

## MARKER LOCATOR ADAPTER

- Depth of cover readings to markers
- Plug-and-play automatic recognition by receiver
- Use when needed – no need for two devices
- Locates balls, disks, full range & near surface markers
- Use as dedicated marker locator or dual utility and marker locator

The **vLoc3-MLA (Marker Locator Adapter)** is designed for easy, fast and accurate location of buried EMS markers. Once located the MLA will give depth of cover to the buried marker (in dedicated marker locate mode) with the touch of a button.

The MLA attaches to the bottom of vLoc3-Pro, vLoc3-XLF, vLoc3-9800 and vLoc3-5000 receivers. When attached and plugged in to the receivers two marker related operating modes are enabled. In the dedicated marker mode, the receiver screens show a peak bar graph with the signal strength from the marker, the marker type and depth to the marker. In the dual marker mode all the above are shown in addition to the standard utility locate screen including left/right arrows and compass.

The plug-and-play MLA will detect any one of nine marker types, in good conditions.



Dedicated Marker Locate Mode Screens



Dual Mode Marker and Utility Locate Screens



vLoc3-Pro      vLoc3-9800      vLoc3-5000      vLoc3-XLF

The MLA works with all vLoc3 series receivers



Simple clip-on and plug-in installation



vLoc3-MLA Marker Locator Adapter Specifications																															
<b>Construction</b>	High impact ABS injection molded housing																														
<b>Weight &amp; Dimensions</b>	1.76lbs (0.8kg), 8.2in(L) x 6.2in(W) x 4in(H) (208mm x 157mm x 102mm)																														
<b>Display</b>	Per vLoc3 series receiver showing: Response to marker balls Marker reference number and icon Circular bar graph and variable pitch tone to indicate signal strength																														
<b>Power</b>	Powered by the vLoc3 series receiver																														
<b>Operating frequencies</b>	<table border="1"> <thead> <tr> <th>Ref #</th> <th>Utility</th> <th>Frequency (Hz)</th> </tr> </thead> <tbody> <tr> <td>1</td> <td> Power (Red)</td> <td>169,800Hz</td> </tr> <tr> <td>2</td> <td> Water (Blue)</td> <td>145,700Hz</td> </tr> <tr> <td>3</td> <td> Sanitary (Green)</td> <td>121,600Hz</td> </tr> <tr> <td>4</td> <td> Telephone (Orange)</td> <td>101,400Hz</td> </tr> <tr> <td>5</td> <td> Gas (Yellow)</td> <td>83,000Hz</td> </tr> <tr> <td>6</td> <td> CATV (Orange/Black)</td> <td>77,000Hz</td> </tr> <tr> <td>7</td> <td> Non-potable Water (Purple)</td> <td>66,350Hz</td> </tr> <tr> <td>8</td> <td> EDF (French Power) (Natural)</td> <td>40,000Hz</td> </tr> <tr> <td>9</td> <td> Power Europe (Blue/Red)</td> <td>134,000Hz</td> </tr> </tbody> </table>	Ref #	Utility	Frequency (Hz)	1	 Power (Red)	169,800Hz	2	 Water (Blue)	145,700Hz	3	 Sanitary (Green)	121,600Hz	4	 Telephone (Orange)	101,400Hz	5	 Gas (Yellow)	83,000Hz	6	 CATV (Orange/Black)	77,000Hz	7	 Non-potable Water (Purple)	66,350Hz	8	 EDF (French Power) (Natural)	40,000Hz	9	 Power Europe (Blue/Red)	134,000Hz
	Ref #	Utility	Frequency (Hz)																												
	1	 Power (Red)	169,800Hz																												
	2	 Water (Blue)	145,700Hz																												
	3	 Sanitary (Green)	121,600Hz																												
	4	 Telephone (Orange)	101,400Hz																												
	5	 Gas (Yellow)	83,000Hz																												
	6	 CATV (Orange/Black)	77,000Hz																												
	7	 Non-potable Water (Purple)	66,350Hz																												
8	 EDF (French Power) (Natural)	40,000Hz																													
9	 Power Europe (Blue/Red)	134,000Hz																													
<b>Operating modes</b>	<ul style="list-style-type: none"> <li>- Line Location Receiver</li> <li>- Marker Locator</li> <li>- Dual mode operation: Peak response combined with Marker-Ball Detection</li> </ul>																														
<b>Environmental</b>	IP54																														

## Compatible Receivers



vLoc3-Pro



vLoc3-9800



vLoc3-5000



vLoc3-XLF

Local Vivax-Metrotech Distributor:

### Vivax-Metrotech Corporation

3251 Olcott Street, Santa Clara, CA 95054, USA

**T/Free: 1-800-446-3392**

**Tel: +1-408-734-3880**

www.vivax-metrotech.com

Tag us on social media @vivax\_metrotech



V1.3

Please visit our website for full product specifications.